

GO-SOUND POCKET MIC

# KIT BODYPACK, HEADSET, AND LAVALIER MIC FOR GO-SOUND AMW - AIR & PROVIBE AIR SPEAKERS

The Go-Sound Pocket Mic is an optional set including a VHF bodypack transmitter, a lavalier microphone, and a headset microphone. It is intended for all of those owners of SOUNDSATION GO-SOUND AMW, GO-SOUND AIR and PROVIBE AIR Active Speakers who need total freedom of movement during their sessions.

GO-SOUND POCKET MIC


67ea81be-9541-4c83-a72a-74aa643a0c06.jpg


49747595-e161-40ea-a198-58efc2b3c97c.jpg

Cardioid Polar Pattern

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

GO-SOUND POCKET MIC

# KIT BODYPACK, HEADSET, AND LAVALIER MIC FOR GO-SOUND AMW - AIR & PROVIBE AIR SPEAKERS

## PRODUCT DETAILS

### KEY FEATURES

- Compatible with Go-Sound 8AMW / 10AMW / 12AMW / 15AMW, Go-Sound 8Air / 10Air / 12Air / 15Air and ProVibe 8Air / 10Air / 12Air / 15Air
- VHF Transmission with SMD Technology
- 175MHz VHF Frequency (NOTE: Before purchasing this product, make sure that the wireless microphone frequency of your Go-Sound 8-10 AMW – or at least one of the two frequencies for Go-Sound AMW 12-15 AMW – is 175MHz)
- Plug and play setup
- 30m ideal distance (without obstacles)
- Simple and lightweight bodypack
- Lightweight Headset with cardioid electret capsule
- Tie Microphone with clip and omni-directional electret capsule

### SPECIFICATIONS

| | |
|---|---|
| **Carrier Frequency** | VHF - 175.00MHz |
| **Transmitter Power** | 10mW |
| **Modulation Type** | FM |
| **Deviation** | 37KHz |
| **Spurious Emission** | > 30dB |
| **Continuous Using** | 7 hours |
| **Frequency Stabilization** | Automatic calibration |
| **Dynamic Range** | > 90dB |

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

GO-SOUND POCKET MIC

# KIT BODYPACK, HEADSET, AND LAVALIER MIC FOR GO-SOUND AMW - AIR & PROVIBE AIR SPEAKERS

| | |
|---|---|
| **Total Harmonic Distortion** | < 0.5% |
| **Frequency Response** | 40Hz~15KHz ±3dB |
| **Input Connector** | 1/8" mono Jack (without thread) |
| **Knobs** | Mic Volume |
| **LED** | Red (battery-low) |
| **Battery Voltage** | 3V (2x1.5V AA Battery) |
| **Headset Microphone** | Cardioid electret capsule |
| **Headset Connector** | 1/8" Mini-Jack (90° without thread) |
| **Lavalier Microphone** | Omni-directional electret capsule |
| **Lavalier Connector** | 1/8" Mini-Jack (without thread) |

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it