




DDJ-1000SRT

4-CHANNEL CLUB-STYLE DJ CONTROLLER FOR SERATO DJ PRO

The 4-channel DDJ-1000SRT inherits the layout of the DDJ-1000, which feels familiar to a CDJ+DJM club-standard set-up. All the same professional features are there too, including low-latency, full-size jog wheels from the CDJ-2000NXS2 and the slick MAGVEL FADER for tight scratching. Concentrate on the crowd, not your laptop, thanks to color On Jog Display, which gives you important track information in the center of each jog wheel. Build excitement on the dancefloor and create huge drops with 4 Sound Color FX and 14 Beat FX. And with 16 Multicolored Performance Pads (8 per deck) at your fingertips, you can trigger various features including Hot Cues, Slicer, and Pitch Play to put your own spin on each track and keep your audience in raptures. If you want to use Serato DJ Pro to play at events and parties and you need a controller that's portable but packed with features, you've found your perfect match in the DDJ-1000SRT. Its multiple inputs and outputs enable you to connect external equipment and assemble different setups, so you'll be prepared for anything.



DDJ-1000SRT

4-CHANNEL CLUB-STYLE DJ CONTROLLER FOR SERATO DJ PRO

PRODUCT DETAILS

KEY FEATURES

Serato DJ Pro compatibility

Full-size jog wheels and MAGVEL FADER

Portable DJ controller with club-style layout

Color On Jog Display

Professional FX

Standalone DJ mixer with multiple inputs and outputs

Multicolored Performance Pads

Key Shift and Key Sync buttons

Aluminum/acrylic-finished top panel

Serato DVS-ready

SPECIFICATIONS

Frequency Response 20 Hz to 20 kHz (LINE)

S/N Ratio 112 dB (USB), 96 dB (LINE), 85 dB (PHONO), 80 dB (MIC)

Total Harmonic Distortion 0.002% (USB), 0.005% (LINE)

Inputs LINE/PHONO x2 (RCA), LINE x2 (RCA), MIC x2 (XLR & 1/4-inch TRS jack x 1, 1/4-inch TRS jack x 1)

Outputs MASTER x2 (XLR x1, RCA x1), BOOTH x1 (1/4-inch TRS jack), PHONES x2 (1/4-inch stereo phone jack x 1, 3.5-mm stereo mini jack x 1)

DDJ-1000SRT

4-CHANNEL CLUB-STYLE DJ CONTROLLER FOR SERATO DJ PRO

USB	USB (Type B) x2
Power Supply	AC adaptor (DC 12V)
Dimensions (WxDxH)	708.0x361.4x73.4 mm
Weight	6.0 Kg
Accessories	AC adapter, Power plug, USB cable, Quick Start Guide, Serato DJ Pro Expansion Pack voucher (Pitch 'n Time DJ)
System requirements	Mac - macOS Mojave 10.14 (updated to the latest version, macOS High Sierra 10.13 (updated to the latest version), macOS Sierra 10.12 (updated to the latest version); Windows - Windows® 10, 8.1, 7 (the latest service pack); CPU Intel® processor Core™ i9, i7, i5, i3 1.07GHz or above; Memory 4GB or more of RAM