

SCENEMAKER 1216 PLUS

12 FIXTURES X 16 CHANNELS DMX INTELLIGENT LIGHTING CONTROLLER

SCENEMAKER 1216 PLUS is a universal intelligent lighting controller. It allows you to manage up to 12 fixtures composed of 16 channels each (192 channels in total), and up to 240 programmable scenes. 6 chases can contain up to 240 steps composed by the saved scenes (the steps) and in any order. Programs can be triggered by music, MIDI, automatically or manually. On the surface you will find various programming tools such as 16 universal channel sliders, quick access scanner and scene buttons, and a LED display indicator for easier navigation of controls and menu functions.

SCENEMAKER 1216 PLUS

[c333ac4f-7efd-4aa9-bf75-e8fd4446193d.jpg](#)

[ad0ed133-1181-40d2-bb44-2618959aaf71.jpg](#)

DMX-512 Control

SCENEMAKER 1216 PLUS

12 FIXTURES X 16 CHANNELS DMX INTELLIGENT LIGHTING CONTROLLER

PRODUCT DETAILS

KEY FEATURES

12 Fixtures with 16 DMX Channels each; 192 Channels in total

23 banks of 8 programmable scenes, 184 scenes in total

6 chases of 184 programmed scenes taken from the 23 banks

Executes multiple chases simultaneously

8 Sliders for direct control of channels

Auto Mode controlled by Speed and Fade Time

Master Blackout

Built-in microphone for Music triggering

LED Display for easy navigation of menus

MIDI control over banks, chases and Blackout

SPECIFICATIONS

Power Supply	DC 9V-12V, 1000mA min.
USB Lamp	5V - 200 mA max
Protocols	DMX-512 USITT
Data Input	locking 3-pin XLR male socket
Data Output	locking 3-pin XLR female socket
Data Pin Configuration	Pin 1 shield, Pin 2 (-), Pin 3 (+)
Controller Size (WxHxD): 482 x 78 x 132 mm	

SCENEMAKER 1216 PLUS

12 FIXTURES X 16 CHANNELS DMX INTELLIGENT LIGHTING CONTROLLER

Net Weight 1.5 kg

Packing Dimension (WxHxD)

550 x 15 x 9.5 mm

Packing Gross Weight

2.0 kg