

ADX-500

ULTRA LOW NOISE ACTIVE DI BOX

The SOUNDSATION ADX-500 ACTIVE BOX is an electronic device that converts an unbalanced audio signal into a balanced signal . You can connect unbalanced input devices like an electric bass, a guitar or a keyboard. The balanced line is less sensitive to electromagnetic interferences and has a better S/N ratio. In this way it is possible to achieve a good performance in case of long distances as well. For instance, it is possible to connect your instrument to a distant mixer maintaining a good quality signal. The ADX-500 is highly recommended for sound engineers and stage/studio performers.

ADX-500

[1ca59149-809a-4d84-8dcc-77e11a22c847.jpg](#)

ADX-500

ULTRA LOW NOISE ACTIVE DI BOX

PRODUCT DETAILS

KEY FEATURES

Converts unbalanced input signal in balanced output signal

Input jack 6,3mm unbalanced

Unbalanced XLR Female Input

Unbalanced 6,3mm Jack Monitor/Link output

Pad 0dB - 20 dB

Balanced XLR Male Output

Ground lift switch

9V battery operated

SPECIFICATIONS

Frequency response	30Hz-20KHz
Maximum input level	0 $\pm$ 20dB
Noise level	= 105 dBU
Power Requirement	AC 20~48V
Battery	9V blockcell 6LR91
Dimension	145X125X59mm
Weight	700 g