

DJM-750MK2

4-CHANNEL MIXER WITH CLUB DNA

Take the step to the DJ booth seamlessly with the DJM-750MK2, a 4-channel mixer which inherits key features and design elements from the DJM-900NXS2, creating a club-style setup when combined with our professional CDJ or XDJ multi players. You can perform seamless mixes on the DJM-750MK2 thanks to the smooth curves on the EQs and channel faders. The Magvel crossfader, inherited from the DJM-900NXS2, gives a precise response and assured feel during even the most complicated scratch techniques.

DJM-750MK2

d0a4fa91-3c81-4055-ad39-aa4d28c2c4ce.jpg

76fe34c4-54c5-404b-918c-b9144372b179.jpg

edfbe56a-cc59-4494-8582-f7f27bc

DJM-750MK2

4-CHANNEL MIXER WITH CLUB DNA

PRODUCT DETAILS

KEY FEATURES

Professional layout

Pro FX with detailed control

Independent send/return

Professional sound quality

Smooth EQs & faders

Rekordbox DJ bundled

Rekordbox DVS bundled

Two headphone outputs

Flexible connectivity

Independent mic section

Included accessories: Power cord, USB cable, Operating instruction, license keys

SPECIFICATIONS

Dimensions	(WxHxD)
Weight	6.6 Kg
Frequency Range	20 - 20000 Hz
Sampling rate	48 kHz
A/D converter	32 bit
D/A converter	32 bit
S/N Ratio	105 dB (line)
Distortion	< 0.005 % (line)

DJM-750MK2

4-CHANNEL MIXER WITH CLUB DNA

Eq/Iso	3 band
Eq/Iso range	Built-in, switchable 3-band equalizer -26dB ~ + 6dB/ 3 band isolator -8 ~ +6 dB
Channels	4
15 effects with adjustable parameters	
Crossfader type	Magvel with 3 assignable fader curves
Inputs	4 PHONO (RCA), 4 LINE/LINE (RCA), 1 MIC (XLR & 1/4 inch TRS Jack)
Send/Return	1 SEND (1/4-inch TS jack), 1 RETURN (1/4-inch TS jack)
USB:1 USB B port + 1 USB A port	
Outputs	2 MASTER (XLR, RCA), 1 BOOTH (1/4 inch TRS Jack), 2 HEADPHONE MONITOR (1/4 inch Stereo Phone Jack, 3.5mm Stereo mini-jack)