ONDA-B840W

40W 70V/100V 8" 2-WAY CEILING SPEAKER WITH BACK CAN


ONDA-B840W


ONDA BW Series offers powerful and accurate coaxial loudspeakers with woofer diameters ranging from 5,25” to 8”, and powers from 20W to 40W RMS. They can be used with standard 70/100V as well as low impedance (8 ohm) professional amplifiers and provide transparent and brilliant sound.

The presence of the back can with a front reflex port allows for an emphasis on the frequency response on the medium-low frequency range, giving a much warmer and more enveloping sound even in the absence of the acoustic box effect due to the ceiling, which is necessary in the case of traditional ceiling speakers.

The housing of GALA BW speakers is made of high-quality ABS. They also feature 0.5” Mylar-dome tweeters, polypropylene enforced woofers.

Installation is very easy, thanks to the quick mounting system with 4 screws. These screws are hidden behind the grill and offer an elegant and minimalist design. The built-in line transformers allow use with 70/100V lines and offer three power taps plus 8ohm to better adapt to different speaker arrangement and amplifier powers. They come in white color but can be painted in any color.


baf5ec6a-f837-401e-86a1-d1cbff7ff13b.jpg


c6e7dd8d-4b68-4858-a7cc-889f15f0bb7d.jpg

70V-100V Line 2-Way Speaker Coaxial Speaker Low Impedance Quick-Fit System

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

ONDA-B840W

40W 70V/100V 8" 2-WAY CEILING SPEAKER WITH BACK CAN

PRODUCT DETAILS

KEY FEATURES

- 2-Way Coaxial Loudspeakers
- Lightweight but Sturdy Frame with back can
- 8” PP Woofer
- 0.5” Mylar Dome Tweeter
- 40W RMS Power
- Built-in 70/100V Line Transformer
- Front selection with 3 Taps, 8 ohms and Off
- Quick-Fit Mounting System
- Angle Coverage: 120°

SPECIFICATIONS

RMS Power	40W
LF Transducer	8” Polypropylene Woofer
HF Transducer	0.5” Tweeter, Mylar Dome
Line Transformer	70/100V
Tapping Powers	40W-20W-10W-OFF-8OHM (100V), 40W-20W-10W-5W-OFF-8OHM (70V)
Frequency Range	40Hz – 20kHz
Sensitivity	92dB (1W@1m)
Cutting Ø	272.00 mm (10.70”)

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

ONDA-B840W

40W 70V/100V 8" 2-WAY CEILING SPEAKER WITH BACK CAN

Speaker Size	Ø300.00 x 205 mm (Ø11,81” x 8.07”)
Speaker Weight	2.46kg (5.42 lbs.)
Packing Size (WxDxH)	308 x 308 x 220 mm (12.12 x 12.12 x 8.66 inches)
Packing Weight	3kg (6.61 lbs.)

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it