

**POKER-350A****350W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER****POKER-350A – Power, Flexibility, and Total Zone Control**

Meet the POKER-350A, a powerhouse **350W 4-zone mixer amplifier** designed for professional multi-room audio installations where performance and reliability are non-negotiable.

With **4 independent 70/100V zone outputs**, each equipped with a **dedicated 5-step attenuator plus Off**, you'll have precise control over every area. Need quick flexibility? Use the **Zone ON/OFF or ALL buttons** to manage coverage instantly.

Seamlessly blend speech and music with **3 Mic/Line inputs**, while **Mic 1 priority with adjustable voice-over** ensures announcements are always heard clearly. Add paging flexibility with **2 call station inputs** and full compatibility with the HMX-MIC paging microphone.

On the media side, the POKER-350A is a true all-in-one player: enjoy **DAB+ digital radio, FM tuner, USB, AUX, and Bluetooth® streaming**—all built right in. Plus, with stereo AUX input, stereo preamp out, and recording outputs, integration with external gear is effortless.

Designed for real-world installations, the POKER-350A also features a standby mode for energy savings without compromising readiness.

Whether it's for hospitality venues, retail, offices, or multi-zone public spaces, the **POKER-350A delivers crystal-clear audio, flexible zoning, and rock-solid reliability—all in one professional package.**



POKER-350A

**350W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER****19''  
Rack**

Wireless



USB



FM

dab+  
DAB+

Bluetooth



48V



70/100V

**Multi  
Zone****Eco  
Friendly**

POKER-350A

## 350W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER

### PRODUCT DETAILS

#### KEY FEATURES

350W Power Amplifier

4-Zones with 70/100V Zone Outputs

Zone Attenuators with 5 positions + Off

Zone ON/OFF and ALL Buttons

3 Mic/Line Inputs

DAB+, USB, FM, AUX, Bluetooth Player

Priority on Mic 1 with Adjustable Voice Over

2 Call Station inputs

Compatible with HMX-MIC Paging Microphone

Stereo Aux In, Stereo Preamp and Rec Outputs

Standby function

### SPECIFICATIONS

**Power Supply** AC 230V-50Hz (IEC)

**Fuse** T5AL 250V

**Power Output** 360W RMS

**Amplifier Construction** Class AB

**Audio Source of Player** USB / AUX / FM / DAB+ / BT

**Inputs** 3x Mic/Line (XLR/Jack), 1xaux (RCA)

POKER-350A

**350W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER**

<b>Line output (REC)</b>	RCA
<b>Zone Outputs</b>	Speaker
<b>Phantom Power</b>	+48V switchable inputs 1-3
<b>Call Station input</b>	2 x RJ45 (for optional HMX-MIC paging stations)
<b>Mute</b>	+24V relay contacts
<b>THD</b>	<0.5% @ 1kHz
<b>Input impedance</b>	1k Ohms (mic)/10k Ohms (line)
<b>Input Sensitivity</b>	-9dB (Line), -41dB (Mic)
<b>SNR</b>	70dB (Line), 70dB (Mic)
<b>BT Version</b>	5.0
<b>Frequency Response</b>	100Hz - 17kHz (-3dB)
<b>Product Size (WxDxH)</b>	433 x 371 x 89 mm (17.04 x 14.6 x 3.5 in.)
<b>Product Size MAX (WxDxH)</b>	485 x 400 x 97 mm (19.09 x 15.7 x 3.8 in.)
<b>Weight</b>	9.8kg (21.6 lbs.)
<b>Package Size (WxDxH)</b>	545 x 475 x 149 mm (21.4 x 18.7 x 5.8 in.)
<b>Package Weight</b>	11.8 kg (26 lbs.)