POKER-350A

350W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER

POKER-350A

POKER-350A – Power, Flexibility, and Total Zone Control

Meet the POKER-350A, a powerhouse **350W 4-zone mixer amplifier** designed for professional multi-room audio installations where performance and reliability are non-negotiable.

With **4 independent 70/100V zone outputs**, each equipped with a **dedicated 5-step attenuator plus Off**, you'll have precise control over every area. Need quick flexibility? Use the **Zone ON/OFF or ALL buttons** to manage coverage instantly.

Seamlessly blend speech and music with **3 Mic/Line inputs**, while **Mic 1 priority with adjustable voice-over** ensures announcements are always heard clearly. Add paging flexibility with **2 call station inputs** and full compatibility with the HMX-MIC paging microphone.

On the media side, the POKER-350A is a true all-in-one player: enjoy **DAB+ digital radio, FM tuner, USB, AUX, and Bluetooth® streaming**—all built right in. Plus, with stereo AUX input, stereo preamp out, and recording outputs, integration with external gear is effortless.

Designed for real-world installations, the POKER-350A also features a standby mode for energy savings without compromising readiness.

Whether it's for hospitality venues, retail, offices, or multi-zone public spaces, the **POKER-350A delivers crystal-clear audio, flexible zoning, and rock-solid reliability—all in one professional package**.

28a9b508-15f3-4003-9730-76816720a6d2.jpg

257f7573-4377-44ca-8bb0-c19616a0f037.jpg

19" Rack Standard Wireless Control USB Player FM Radio DAB+ Bluetooth Phantom Power 70V-100V Line Multi-Zone Syst

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

POKER-350A

350W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER

PRODUCT DETAILS

KEY FEATURES

- 350W Power Amplifier
- 4-Zones with 70/100V Zone Outputs
- Zone Attenuators with 5 positions + Off
- Zone ON/OFF and ALL Buttons
- 3 Mic/Line Inputs
- DAB+, USB, FM, AUX, Bluetooth Player
- Priority on Mic 1 with Adjustable Voice Over
- 2 Call Station inputs
- Compatible with HMX-MIC Paging Microphone
- Stereo Aux In, Stereo Preamp and Rec Outputs
- Standby function

SPECIFICATIONS

Power Supply	AC 230V-50Hz (IEC)
Fuse	T5AL 250V
Power Output	360W RMS
Amplifier Construction	Class AB
Audio Source of Player	USB / AUX / FM / DAB+ / BT
Inputs	3× Mic/Line (XLR/Jack), 1×aux (RCA)

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

POKER-350A

350W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER

Line output (REC)	RCA
Zone Outputs	Speaker
Phantom Power	+48V switchable inputs 1-3
Call Station input	2 x RJ45 (for optional HMX-MIC paging stations)
Mute	+24V relay contacts
THD	<0.5% @ 1kHz
Input impedance	1k Ohms (mic)/10k Ohms (line)
Input Sensitivity	-9dB (Line), -41dB (Mic)
SNR	70dB (Line), 70dB (Mic)
BT Version	5.0
Frequency Response	100Hz - 17kHz (-3dB)
Product Size (WxDxH)	433 × 371 × 89 mm (17.04 x 14.6 x 3.5 in.)
Product Size MAX (WxDxH)	485 x 400 x 97 mm (19.09 x 15.7 x 3.8 in.)
Weight	9.8kg (21.6 lbs.)
Package Size (WxDxH)	545 × 475 × 149 mm (21.4 x 18.7 x 5.8 in.)
Package Weight	11.8 kg (26 lbs.)

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it