

REPO-240A

240W SINGLE-ZONE MULTI-PURPOSE MIXER AMPLIFIER

REPO-240A

REPO-240 – Powerful. Versatile. Always in Control.

The **REPO-240A** is a **240W single-zone multi-purpose mixer amplifier** built to deliver crystal-clear sound, rock-solid reliability, and the flexibility your installation demands.

With its **8-channel mixer** at the core, the REPO-240A gives you seamless integration of multiple sources. It features **2 Mic/Line inputs** for microphones or balanced sources, plus **4 stereo line inputs** for music players, media devices, or external processors – making it ideal for both speech and music applications.

Driving up to **240 watts of Class-D power**, this amplifier ensures efficiency and clean performance across **70V, 100V, and low-impedance (4?) outputs**, adapting easily to a wide range of system designs.

For paging and announcements, the REPO-240A includes a **dedicated paging microphone with chime and voice-over function**, so messages cut through the mix with clarity. Add flexibility with a **line output**, plus **emergency input** and **24V priority control output**, ensuring critical announcements always take precedence.

Energy-conscious? The built-in **auto-standby function** reduces power consumption while keeping the system instantly ready.

From corporate facilities to retail stores, schools, and hospitality environments, the **REPO-240A delivers powerful amplification, intuitive control, and versatile connectivity—all in a single professional package.**

IsGqoDNs6frdzqL1768405264_Repo 240A_front.jpg



macrLBWE0dYbH01768405269_Repo 240A_rear.jpg

REPO-240A

240W SINGLE-ZONE MULTI-PURPOSE MIXER AMPLIFIER

PRODUCT DETAILS

KEY FEATURES

8-Channel Mixer

2 Mic/Line Inputs with 2-Band EQ and 48V Phantom

4 Stereo Line Inputs with 2-Band EQ

240W Class-D Power Amplifiers

70V, 100V and 4ohm Outputs

Paging Microphone with Chime and Mic/Line button

Voice Over on Mic 1 and Paging Mic Input

Emergency 0dB Input with Mute All and Voice over controls

24V Priority Control Out

80Hz Low-Cut Filter

Stereo Preamp Out

Auto-Standby Function

SPECIFICATIONS

Power Supply AC 170 V-240V 50Hz/60Hz (IEC)

Fuse T3.15AL 250V

Power Output 240W RMS

Amplifier Class D + Transformer Outputs

Construction

REPO-240A

240W SINGLE-ZONE MULTI-PURPOSE MIXER AMPLIFIER

Inputs	1x Emergency (Euroblock terminal), 1x Paging Mic, 1x Mic A (XLR/Jack), 1x Mic B (XLR/Jack), 4x RCA
Line Output (REC)	1x RCA, 0dBV
Speaker Outputs	70V/100V and 4Ω (Euroblock terminals)
Filter	Selectable 80Hz Low Cut (18 dB/oct)
Phantom Power	+48V (Mic A, Mic B)
THD	<0.7% @ 1kHz
Input Impedance	1kΩ (Mic), 10kΩ (Line)
Frequency Response	80 Hz - 20kHz (-3 dB)
Control Output	24VDC Max 0.5A on Emergency Mute All and Paging contact closure
Product Size (W x D x H)	433 x 185 x 90 mm / 17.04 x 7.28 x 3.54 in
Weight	5.6 kg
Package Size (W x D x H)	530 x 341 x 129 mm / 20.87 x 13.42 x 5.08 in
Package Weight	13.7 kg