70436

2 PORT AUTOMATIC OPTICAL AUDIO SWITCH

The Lindy 2 Port Automatic Optical Audio Switch allows users to connect two digital optical Toslink sources to a single optical TosLink (SPDIF) input on an AV amplifier, Hi-Fi or home cinema system. The optical switch will automatically detect the live signal and switch to this channel.

Ideal for use with games consoles, HD players, set top boxes, PC_s etc. and saves on wear and tear of constant plugging and unplugging of cables.

Please note: TosLink cables are not included.

11de9196-2eb1-4445-8627-e193ebc68c4e.png

70436

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

70436

2 PORT AUTOMATIC OPTICAL AUDIO SWITCH

PRODUCT DETAILS

KEY FEATURES

- Connects two digital optical Toslink sources to a single optical Toslink input
- Automatic or manual switch function
- Input ports: 2 x Toslink (Optical Fibre)
- Output Ports: 1 x Toslink (Optical Fibre)
- 2 year warranty

SPECIFICATIONS

AV Interface	TosLink
Supports Bandwidth	32 - 96kHz
Supported Audio	U ncompressed PCM / LPCM, Dolby AC-3, Dolby 5.1, Dolby Digital and DTS
Special Features	Automatic switching of active ports
Input	2 x TosLink (Optical Fibre)
Output	1 x TosLink (Optical Fibre)
Power	5.5/2.1mm DC socket
Dimensions (approx.) WxDxH	75x65x30mm (2.95x2.56x1.18in)
Housing Material	Plastic
Net Weight	0.055kg (0.12lb)
Operating Temperature	0°C - 50°C (32°F - 122°F)
Storage Temperature	-20°C - 70°C (-4°F - 158°F)
Humidity	20 - 80% RH (non-condensing)
Power Requirements	5VDC 1.2A

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

70436

2 PORT AUTOMATIC OPTICAL AUDIO SWITCH

Colour	Black

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it