

VOXTAKER 100

LARGE-DIAPHRAGM STUDIO MICROPHONE WITH CARDIOID POLAR PATTERN

Professional condenser microphone featuring true condenser capsule with cardioid polar pattern. It can be used with confidence in a variety of professional applications, such as recording studios, broadcasting, podcasting, and stage performances. With its gold-plated diaphragm capsule and premium FET preamp circuitry, VoxTaker 100 has very low self-noise and high output, to reproduce even the subtle sound and fulfil the requirement of high sound quality for broadcasting and recording. The package includes Shock-Mount and Pop Filter, all inside a plastic case.



VOXTAKER 100

LARGE-DIAPHRAGM STUDIO MICROPHONE WITH CARDIOID POLAR PATTERN

PRODUCT DETAILS

KEY FEATURES

34mm Gold-Plated Pressure Gradient Transducer

Cardioid Polar Pattern

High Quality FET Preamp Stage

High Absorption Shock-mount

Stylish and Innovative Pop Filter

Plastic Case

SPECIFICATIONS

Element	34mm pressure gradient capsule	
Cardioid Polar Pattern		
Frequency Response	30Hz - 20kHz	
Sensitivity	-38dB (0dB = 1V/Pa at 1kHz)	
Output Impedance	150 (at 1kHz)	
Load Impedance	1000 ohms	
Self-Noise	16dB A-weighted	
Max Input SPL	130dB (@ 1kHz - 1% T.H.D.)	
S/N Ratio	78dB	
Microphone Size (WxHxD)	188x50x50 mm	
Microphone Weight	272 g	

VOXTAKER 100

LARGE-DIAPHRAGM STUDIO MICROPHONE WITH CARDIOID POLAR PATTERN

Case Size (WxHxD)

340 x 280 x 90 mm

Package Weight (Mic., case and accessories)

1.5kg