WF-U404HP A1

UHF TRUE DIVERSITY 4-CH WIRELESS SYSTEM – 2 HANDMIC – 2 BODYPACK & HEADSET A1 (516-558 MHZ)

WF-U404HP A1

Small but mighty – that's how the new Soundsation WF-U400 True Diversity UHF wireless microphone systems are described in a nutshell. Each receiver, housed in a half-rack 19" metal case, can accommodate up to four reception channels. Each has its own color-changeable backlit display for easy recognition of the respective transmitter. A rack-mount kit also allows two receivers, for a maximum of eight channels in a single 19" rack.


In terms of audio quality, the system offers crystal-clear sound and flawless performance, even in crowded environments. Thanks to the True Diversity UHF reception circuit, the system controls two antennas for stable, uninterrupted audio. Furthermore, the 300 selectable frequencies, the PLL (Phase-Locked Loop) frequency synthesis ensures consistent, interference-free performance even up to 16 channels simultaneously, provided they are well distributed between the approximately 40MHz of the A1 (516-558MHz) and A2 (626-668MHz) bands, and in the absence of large physical obstacles.


With a range of 40 to 60 meters (depending on interference and obstacles), automatic or manual frequency scanning options, and a quick infrared pairing procedure, the WF-400 systems are designed for easy setup and use.


The handheld transmitter, sturdy yet unobtrusive, features an LCD display with color-changing backlighting depending on the channel it is paired to. The professional dynamic capsule has a cardioid polar pattern and is suitable for both singing and simple close-up vocal pickup.

The compact and lightweight pocket transmitter features a flesh-colored headband microphone with a cardioid condenser capsule. The connection is via a 3-pin mini-XLR. Like the handheld microphone, the bodypack also has an LCD display with color-changing backlighting depending on the channel it is paired to.

The Soundsation WF-U400 systems therefore allow you to cover an infinite number of audio micing applications where many channels, high reliability and maximum ease of use are required.


WF-U404-Receiver-3QtrR_tn.jpg


WF-U404-Receiver-Front_tn.jpg


WF-U404-Receiver-Rear_tn.jpg

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

WF-U404HP A1

UHF TRUE DIVERSITY 4-CH WIRELESS SYSTEM – 2 HANDMIC – 2 BODYPACK & HEADSET A1 (516-558 MHZ)

PRODUCT DETAILS

KEY FEATURES

- UHF True Diversity Receiving Circuitry
- PLL phase-locked frequency synthesis
- 300 selectable frequencies or with automatic scanning
- Stable Performance with 40-60m Operating Distance
- Integrated Antenna Distribution System
- Quick IR Pairing Procedure
- 4-Channel Systems
- 516-558MHz (A1) Band Operation
- Transmission bandwidth: < 100kHz
- 1” TFT Color Display for each transmitter
- Adjustable background color for each Tx and Rx Channels
- Half 19” Rack-mount Receiver (rack kit optional)
- Elegant and rugged handheld transmitter
- Low noise handling microphone
- Cardioid dynamic cartridge
- Bodypack with rugged and stylish case
- Mini-XLR with adjustable gain
- Headset mic with cardioid condenser capsule
- Professional carring case

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

WF-U404HP A1

UHF TRUE DIVERSITY 4-CH WIRELESS SYSTEM – 2 HANDMIC – 2 BODYPACK & HEADSET A1 (516-558 MHZ)

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

WF-U404HP A1

UHF TRUE DIVERSITY 4-CH WIRELESS SYSTEM – 2 HANDMIC – 2 BODYPACK & HEADSET A1 (516-558 MHZ)

SPECIFICATIONS

Receiving Channels	4CH
Carrier Frequency	516-558 MHz (A1)
Oscillation	PLL phase-locked frequency synthesis
Frequency Sensitivity	Input 6dBµV, S/N>80dB
Operating Distance	40-60 meters
T.H.D. (Total Harmonic Distortion)	<0.5%@1kHz
Transmission Bandwidth	< 100kHz
Receiver Display	4x 28x13.5mm TFT Color Display
Receiver Power Supply	DC 12-18V - 1000mA
Receiver Dimensions (WxDxH)	200 x 205 x 45 mm
Max Receiver Dimensions (WxDxH)	210 x 20,5 x 160 mm (antennas included)
Packing Dimensions (WxDxH)	465 x 100 x 365 mm
Packing Gross Weight	3,7 kg
Handmic Pickup Gain	Fixed Gain
Handmic Transmission Power	13dB
Handmic Current Drain	Standard <130mA
Handmic Display	LCD
Handmic Cartridge	Dynamic Cardioid
Handmic Batteries	2x 1.5V AA-Type
Handmic Dimensions (W/DxH)	Ø50 x 251 mm (1.97 x 9.88” in.)
Handmic Net Weight	0.4 kg with batteries (0.88 lbs.)
Bodypack Pickup Gain	Adjustable Gain

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it