

MIOMIX 202M

# 4-CHANNEL PROFESSIONAL AUDIO MIXER WITH MEDIA PLAYER, BT & DIGITAL ECHO EFFECT

MioMix 202M is a 4-channel mixer with USB player ideal for small home recording, live gigs and podcasting applications that require professional quality level and maximum portability. Two Mic inputs are equipped with noise-less preamps that accepts all main sound sources, such as condenser microphones - thanks to the +48V Phantom Power, dynamic mics, line and high-impedance inputs (guitars, basses, etc.). A stereo line input allow you to connect keyboards, CD players, DJ consoles, tablets, smartphones, etc. The USB & BT player accepts WAV, MP3, WMA and FLAC format audio files, as well as wireless audio streaming (BT). It also records your gig in MP3 format (48kHz/16bit @ 128Kbps). The professional echo digital effect enriches your performance by allowing you to adjust speed and number of repetitions. An indispensable and reliable tool for all small audio applications.



MIOMIX 202M

# 4-CHANNEL PROFESSIONAL AUDIO MIXER WITH MEDIA PLAYER, BT & DIGITAL ECHO EFFECT

## PRODUCT DETAILS

### KEY FEATURES

4 Total Channels

2 Mic/Line channels with noiseless preamp, combo connector, Hi-Z input for guitars, +48V Phantom Power, Peak Indicator

1 Stereo Line Channel with 1/4" Jack inputs, +4/-10dB Pad Adapter and Peak Indicator

USB Media Player and Recorder (WAV, MP3, WMA, FLAC and BT wireless audio streaming)

2-Band EQ for channels 1 and 2

Digital Echo Effect with Repetition, Delay and Level adjustment

Media Player output level control

Headphone monitor out with level control

XLR Main Outputs with Master Level Control

Stereo 6-Led VU Meter Bar

Rugged and Lightweight Metal Case for Maximum Flexibility and Portability

### SPECIFICATIONS

<b>Input Connections</b>	Balanced XLR/Jack Combo (Channel 1-2), Balanced 1/4" Jack (Channel 3-4)
<b>Output Connection</b>	Balanced XLR (Main Out L-R), Stereo 1/4" Jack (Phones)
<b>Channel 1-2 Functions</b>	+48V Phantom Power, Impedance switch (Line/Hi-Z), 2-Band EQ (80Hz/12kHz +/-15dB), Effect Send Level, Pan Position, Channel Volume, Peak Led Indicator
<b>Channel 3-4 Functions</b>	Impedance switch (+4/-10dB), 2-Band EQ (80Hz/12kHz +/-15dB), Effect Send Level, Pan Position, Channel Volume, Peak Led Indicator

MIOMIX 202M

# 4-CHANNEL PROFESSIONAL AUDIO MIXER WITH MEDIA PLAYER, BT & DIGITAL ECHO EFFECT

<b>USB Player Buttons</b>	Up/Rewind, Down/Forward, Play/Pause/Enter, Menu
<b>USB Player Functions</b>	BT streaming, Music Player, Audio Recording, EQ-Curve Selection
<b>USB Drive Format</b>	FAT32 format – max 64GByte
<b>Player File Formats</b>	WAV, MP3, WMA, FLAC e streaming audio wireless BT
<b>Recorder File Format</b>	MP3 (48kHz/16bit @ 128Kbps)
<b>Effect Functions</b>	Echo Repetition Adjustment, Echo Delay Time Adjustment, Echo Level Adjustment
<b>Level Meter</b>	2x6 LED Meter
<b>Max Output Level</b>	3 Vrms
<b>Frequency Response</b>	+/-0.5dB, 20Hz-20kHz
<b>Dynamic Range</b>	102dB
<b>THD+N @ 1kHz</b>	=0.003%
<b>Stereo Crosstalk</b>	92dB
<b>Power Requirements</b>	DC 5V, 1A
<b>Power Consumption</b>	Max. 2.5W
<b>Size (WxDxH)</b>	166 x 165 x 66 mm
<b>Packing Size (WxDxH)</b>	300 x 208 x 87 mm
<b>Net Weight</b>	0.9 kg
<b>Gross Weight</b>	1.2 kg