

CLUB XS5+ 5-CHANNEL MIXER WITH ECHO AND PLAYER

Compact, portable mixing console featuring 5 inputs, Bluetooth connectivity, on-board Echo effects and USB/SD card playback and recording functions. 3 band EQ, 1 auxiliary, balanced mic/line connectors, compressor control, and 2 band EQ with 1 auxiliary for both stereo channels. There are also balanced XLR connectors for the main outputs, jack outputs for control room, and phono connectors for record and playback.

Ultra-compact, lightweight, high quality and extremely versatile, the Club XS 5+ is the perfect mixer for any live performance and home recording situation.



FRENEXPORT

Via Enzo Ferrari 10 62017 Porto Recanati (MC), Italy info@frenexport.it



CLUB XS5+ 5-CHANNEL MIXER WITH ECHO AND PLAYER

PRODUCT DETAILS

KEY FEATURES

2 inputs (1 mic channels, 2 stereo channels)

1 Auxiliary bus for monitoring and internal effect

Professional balanced outputs

High quality microphone pre amp with enhanced compression and gain controls and 3 band EQ

Echo effect

Bluetooth playback connectivity

USB/SD media player and recorder

SPECIFICATIONS

Inputs	5 (1 Mic Inputs, 2 Stereo Inputs)
Mic Gain Range	6dB to 50dB
Line Gain Range	10dB to 34dB
EIN	-100dB
Frequency Response	10Hz – 20kHz (+1/-3dB)
THD Mic Channel	<0.1%
Signal to Noise Ratio	80dB
Output Levels	Max +26dB (Bal), +20dB (unBal)
EQ	Hi 12kHz, Mid 2.5kHz, Lo 45Hz
USB/SD	MP3 Audio playback
Record	To USB drive or SD card (128kbps mono)
DSP Effects	Echo effect

FRENEXPORT

Via Enzo Ferrari 10 62017 Porto Recanati (MC), Italy info@frenexport.it



CLUB XS5+ 5-CHANNEL MIXER WITH ECHO AND PLAYER

Power supply

100-240 Vac - 50/60Hz

Dimension (WxDxH)

195 x 80 x 270 mm

FRENEXPORT

Via Enzo Ferrari 10 62017 Porto Recanati (MC), Italy info@frenexport.it