

VERBA-401 A1

VERBA-401 UHF TRUE DIVERSITY WIRELESS SYSTEM WITH AUTOSCAN – 4 HANDMIC A1 (516-558 MHZ)

VERBA-401 A1

The VERBA Series UHF True Diversity Wireless System with Autoscan is a game-changing solution for anyone needing reliable, high-quality wireless audio. Perfect for live performers, sound engineers, and event organizers, it offers crystal-clear sound and flawless performance, even in crowded signal environments.

With its UHF True Diversity receiving circuitry, the system monitors two antennas for stable, uninterrupted audio. Plus, the PLL (Phase-Locked Loop) frequency synthesis ensures consistent, interference-free performance. Offering an operating range between 40 and 60m (depending on interferences and obstacles), Autoscan or manual frequency scanning options, and a quick IR pairing procedure, it's designed for easy setup and use. Its vibrant 2.5" TFT display on the receiver and 1" displays on each transmitter provide real-time feedback, while a 7-band adjustable EQ processor lets you fine-tune your sound. Customizable display colors and a 19" rack-mount receiver add a personal touch and professionalism to any setup.

Whether you're performing live or broadcasting, this system delivers reliable, clear audio with ease and precision.

5f6b0649-1235-44e8-81ca-d9e867ebc38b.png

602b9be1-1240-4b11-8ed0-ec9fceb85706.png

ac791ae4-8512-4a46-82df-0782

19" Rack Standard

VERBA-401 A1

VERBA-401 UHF TRUE DIVERSITY WIRELESS SYSTEM WITH AUTOSCAN – 4 HANDMIC A1 (516-558 MHZ)

PRODUCT DETAILS

KEY FEATURES

UHF True Diversity Receiving Circuitry

PLL phase-locked frequency synthesis

Stable Performance with 40-60m Operating Distance

Integrated Antenna Distribution System

Automatic or Manual Frequency Scan

Quick IR Pairing Procedure

2-Channel and 4-Channel Systems available

516-558MHz Band Operation

Transmission bandwidth: < 100kHz

Main 2.5" TFT Color Display

1" TFT Color Display for each transmitter

7- band adjustable EQ processor

Adjustable background color for each Tx and Rx Channels

19" Rack-mount Receiver

Elegant and rugged handheld transmitter

Low noise handling microphone

Cardioid dynamic cartridge

Transmission Power: 10mW

VERBA-401 A1

VERBA-401 UHF TRUE DIVERSITY WIRELESS SYSTEM WITH AUTOSCAN – 4 HANDMIC A1 (516-558 MHZ)

SPECIFICATIONS

Receiving Channels	4CH
Carrier Frequency	516-558MHz (A1)
Oscillation	PLL phase-locked frequency synthesis
Frequency Sensitivity	Input 6dBμV, S/N>80dB
Operating Distance	40-60 meters (depending on interferences and obstacles)
Sound Processing	7-band adjustable EQ
T.H.D. (Total Harmonic Distortion)	<0.5%@1kHz
Transmission Bandwidth	< 100kHz
Receiver Display	TFT Color Display
Receiver Power Supply	DC 12-18V - 1000mA
Receiver Dimensions (W/Max WxDxH/Max H)	410/483 (with rack adapters) x 207 x 50/250 (with antennas) mm (16.14/19.01 x 8.15 x 1.97/9.84" in.)
Packing Dimensions (WxDxH)	530 x 387 x 70 mm (20.87 x 15.24 x 2.75" in.)
Packing Gross Weight	3.4 kg (7.49 lbs.)
Handmic Pickup Gain	Fixed Gain
Handmic Transmission Power	13dB
Handmic Current Drain	Standard <130mA
Handmic Display	LCD
Handmic Cartridge	Dynamic Cardioid
Handmic Batteries	2x 1.5V AA-Type
Handmic Dimensions (W/DxH)	Ø50 x 251 mm (1.97 x 9.88" in.)
Handmic Net Weight	0.4 kg with batteries (0.88 lbs.)