

HMX-44 PLAY

RACKMOUNT 4-IN / 4-OUT MATRIX MIXER WITH MULTI-PLAYER

HELVIA has thought to respond to the main needs of those involved in small-to-medium audio installations offering versatility and compactness in an integrated solution such as the HMX-44.

This is a little gem that integrates a matrix with a 4-input, 4-output mixer and a multimedia player. The mixer section provides 3 combo Mic-Line inputs with 48V Phantom, a front mini-jack stereo Line input combined with the multimedia player with DAB+, FM, USB, BT. Each input has independent level adjustment, and the 3 combo Mic/Line inputs also feature high and low tone adjustment.

All 4 inputs are assigned independently to the 4 zones, and each zone has output level control.

The HMX-44 provides connection with HMX-MIC microphone base station via RJ-45 connection. The station is equipped with alert chimes and allows the 4 zones to be selected independently.

HMX-44 PLAY

[08366359-9cd9-4df3-9088-2b00f5e03598.jpg](#)

[dd2fc5fe-8eec-482f-85cd-799e64bbc372.jpg](#)

[cb3b748b-db92-4c6f-aff8-3acd9e83a](#)

Multi-Zone System RDS

FM Radio

DAB+

Bluetooth

Wireless Control Phantom Power DSP

19" Rack Stand

HMX-44 PLAY

RACKMOUNT 4-IN / 4-OUT MATRIX MIXER WITH MULTI-PLAYER

PRODUCT DETAILS

KEY FEATURES

4-In / 4-Out Matrix

4-channel mixer with 3 combo Mic/Line inputs and 1 Mini-jack Stereo Front input

RCA Line Outputs

Multimedia Player with DAB+, FM, USB, BT and Remote Control

48V Phantom Power for condenser microphones and Priority on Mic 1

Small size in 1 rack unit

Mute function in case of emergency

SPECIFICATIONS

Frequency response	100Hz - 24kHz
THD	<0.76% @ 1kHz
Input impedance	1k Ohms (mic/line)
Input sensitivity	-11dB (line), -46dB (mic)
SNR	84dB (line), 82dB (mic)
Inputs	1Mic (XLR), 2 x mic/line (XLR/jack), 1 Line (RCA/Euro-block terminal)
Zone Line Outputs	4 x RCA (mono) outs
Multimedia Player	DAB+/FM/USB/BT
Phantom power	+48V switchable on each XLR Input
Mute	+24V Relay Contacts

HMX-44 PLAY

RACKMOUNT 4-IN / 4-OUT MATRIX MIXER WITH MULTI-PLAYER

Bluetooth Version	2.0
Call Station Port	RJ45 Port (with power)
Power supply	170-264Vac, 50Hz (IEC)
Fuse	T1A/250V
Unit Dimensions	435 x 122 x 44mm (17.1 x 4.8 x 1.7 in)
Packing Dimensions	550 x 227 x 69 mm (21.6 x 8.9 x 2.7 in)
Weight	1.8 kg – 4 lbs.
Packing Weight	2,74 kg – 6 lbs.