

DJM-V10-LF

CREATIVE STYLE 6-CHANNEL PROFESSIONAL DJ MIXER WITH LONG FADER

The DJM-V10-LF features new, longer channel faders with optimized curves and a new custom-designed curve preset to enable you to perform smooth and accurate mixes. The 60 mm shaft slide faders enable you to control the volume of the audio source from each channel precisely. What's more, a brand-new fader curve setting has been added to the unit and the faders have been appropriately weighted to enhance the potential offered by their elongated range. All the other features and specifications of the DJM-V10-LF are the same as the DJM-V10, which has become popular with the most creative DJs since its release in early 2020. The 6-channel unit is loaded with unique features and produces warm audio with energy and presence.

DJM-V10-LF

[c7af5f08-fc92-492b-a9d2-c17cb507b3c3.png](#)

[c68f8481-f4a4-4ee8-9243-8d42682de24c.png](#)

[3bcd21a2-622b-478b-adcb-7eed8](#)

DJM-V10-LF

CREATIVE STYLE 6-CHANNEL PROFESSIONAL DJ MIXER WITH LONG FADER

PRODUCT DETAILS

KEY FEATURES

60mm shaft slide fader

Unique fader curve

Elite sound quality

6 channels with a wide range of inputs

4-band Eq and compressor

Effects for more creative expression

3-band master isolator

Dual headphones output and booth Eq

Lockable power cable

DJM-REC compatible

Rekordbox's low-latency

Serato DVS-ready (not included)

TRAKTOR DVS-ready (not included)

The DJM-V10 supports the extended PRO DJ LINK ShowControl protocol

SPECIFICATIONS

6 channels

EQ 4 band

EQ Range [Hi/Low] -8 ~ +6 dB / [Hi Mid/Low Mid] -26 dB ~ +6 dB dB

DJM-V10-LF

CREATIVE STYLE 6-CHANNEL PROFESSIONAL DJ MIXER WITH LONG FADER

Frequency range	20 - 40.000 Hz
Sampling Rate	96 kHz
A/D Converter	32 bit
D/A Converter	32 bit
S/N Ratio	Line 105 dB
S/N Ratio	Phono 88 dB
S/N Ratio	Mic 79 dB
Distorsione	< 0,005 % (LINE)
Filter	HPF, LPF
MULTI I/O	1/4-inch jack, USB (Type A)
Beat FX	Delay, Echo, Ping Pong, Spiral, Helix, Reverb, Shimmer, Flanger, Phaser, Filter, Trans, Roll, Pitch, Vinyl Brake, FX Frequency, X-Pad, Rekordbox Quantize, Master Isolator
ProDJ Link, Booth EQ, P-Lock Fader Caps, Auto Standby	
DVS Control	rekordbox, Serato DJ Pro, TRAKTOR PRO 3
Mic Connection	XLR / 1/4-inch Jack Combo, 1/4-inch TRS Jack
Talkover	3 Position Switch
Talkover Attenuator	
Full assignable MIDI controls	
Input	6 DIGITAL (Coaxial), 6 LINE (RCA), 4 FONO (RCA)
Send/Return	3 SEND (1/4-inch TS jack), 3 RETURN (1/4-inch TS jack)
LAN	1; USB
Outputs	2 MASTER (XLR, RCA), 1 BOOTH (1/4 inch TRS Jack), 4 HEADPHONE MONITOR (1/4 inch Jack, mini-jack), 1 REC OUT (RCA), 1 DIGITAL (AES/EBU), 1 MIDI (DIN)