


WF-LM10 MINI-XLR

CARDIOID LAVALIER MICROPHONE WITH ELECTRET CAPSULE (3-POLE MINI-XLR CONNECTOR)

This microphone is specifically designed for conferences, presentations, live events and in general in combination with wireless systems whose transmitter is bodypack type. The Electret capsule with Cardioid polar pattern allows a good voice pickup and avoids the Larsen effect, which is very frequent in these applications. The good sensitivity and the excellent frequency response make the voice natural (no nasal sound) without increasing a lot the preamplifier gain.

The microphone is equipped with a windscreens foam, unobtrusive clip and 3-Pole Mini-XLR Connector. It is designed for combination with Soundsation WF-U2602PP, WF-U2302HP, WF-U2302PP, WF-D190P MKII, WF-D190P, WF-D290HP MKII, WF-D290HP MKII-A2, WF-D290HP bodypacks (check the compatibility list and visit www.soundsation.com for any new models) and, in general, with all those pocket transmitters with 3-Poles Mini-XLR connector (see connection details in the Specification)



WF-LM10 MINI-XLR

CARDIOID LAVALIER MICROPHONE WITH ELECTRET CAPSULE (3-POLE MINI-XLR CONNECTOR)

PRODUCT DETAILS

KEY FEATURES

Specifically designed for conferences, presentations and live events

Compatible with Soundsation U2602PP, WF-U2302HP, WF-U2302PP, WF-D190P MKII, WF-D190P, WF-D290HP MKII, WF-D290HP MKII-A2, WF-D290HP BODYPACKS

1/8" (3.5mm) TS Screw-lock Jack connector for wireless bodypacks

Electret Capsule with Cardioid polar pattern

Foam windscreens

Unobtrusive small clip for attaching to clothing

Compact, discreet design

SPECIFICATIONS

Impedance 680 Ω ± 10%

Sensitivity -37dB ± 2dB

Frequency Response 20Hz - 20kHz

Directivity Uni-directional Cardioid

Working Voltage From 1.0V to 10V

Connector 3-Pole Mini-XLR

Connector Details (1) = Ground; (2) & (3) = Signal (Phantom Power is 3V)

Wire Rod ?=2.3mm / L=1.2m