

4LEDKIT-PARTY 2

COMPLETE 4-PAR LED LIGHTING KIT

SOUNDSATION 4LEDKIT-PARTY 2 brings you a complete light system including all accessories in only one package. It is the smartest solution for all musicians, DJs, and small rental companies. It comes complete with 4 compact LED spots. Each spot contains 81 LEDs (27 Red, 27 Green, 27 Blue) in order to create a complete color palette. The spots are mounted on a T-bar which has a built-in controller unit. The T-bar can be controlled by the included wireless pedal-board or by DMX. In addition to RGB color adjustment of all four PARs independently, the unit features 12 auto running programs and 4 Audio Mode Options, to let your lighting kit create wonderful effects even without a DMX controller.

4LEDKIT-PARTY 2

[ab96bdbd-18db-415e-b831-910d1d14a2cf.jpg](#)

[8c9e7e3a-f8a9-4ee7-ac92-e6be33c2bdaa.jpg](#)

[20de2c81-d026-4539-a2db-9db777](#)

Wireless Control

4LEDKIT-PARTY 2

COMPLETE 4-PAR LED LIGHTING KIT

PRODUCT DETAILS

KEY FEATURES

- 4 PARs with 81 high-brightness LED each (27R, 27G, 27B)
- T-Bar with internal controller and power unit (carrying bag included)
- 2.2m max Tripod Stand with carrying bag included
- Operation Modes: Auto, Sound, DMX, Footswitch modes
- 12 Internal Programs
- DMX: 15CH mode or 3CH basic mode (only RGB control on all PARs)
- 4 kinds of Audio Mode with internal Microphone and sensitivity adjustment
- Beam Angle: 16° (per PAR)
- Field Angle: 26° (per PAR)
- LED Display for easy navigation and programming
- Wireless Pedalboard with 2 footswitch

SPECIFICATIONS

LED per single PAR	27 red 625nm/100mW, 27 green 525nm/120mW, 27 blue 465nm/120mW
Beam angle	16° (per PAR)
Field angle	26° (per PAR)
DMX Channels	3, 15CH
AC power	100V-240V 50/60Hz Switching Power Supply
Power Consumption	30W
Fuse	1.6A slow
Power Linking	30pcs @ 240V, 15pcs @ 110V

4LEDKIT-PARTY 2

COMPLETE 4-PAR LED LIGHTING KIT

Bar Size	910x242x48 mm
Packing (LxHxW)	1180x125x350 mm
G.W	10 kg