

WF-V11PD

## VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (209.8 MHZ)

WF-V11 is the answer to all those who need a reliable, high-quality sound, and easy to use wireless microphone system. Ideal in educational, Portable Sound, Public Address, and DJ contexts, the WF-V11 impresses with its brilliant and warm sound, thanks to the quality of components and the capsule designed for all application.

WF-V11PD

cb05ccd6-bb41-44ae-b798-4ef3d8f5f2a7.jpg

3617244f-50b0-4609-90b4-613ef85b3142.jpg

WF-V11PD

# VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (209.8 MHZ)

## PRODUCT DETAILS

### KEY FEATURES

VHF Transmission with SMD Technology

4 available Frequencies in VHF Band

Simple user Interface for plug and play setup

30m ideal distance (without obstacles)

Strong yet lightweight bodypack transmitter

Professional and Lightweight Headset with high-sensitivity dynamic cardioid capsule

### SPECIFICATIONS

|                            |                           |
|----------------------------|---------------------------|
| Carrier Frequency          | VHF 200 - 215.3 MHz       |
| Operating Frequency        | 209.8 MHz                 |
| Frequency Stabilization    | Automatic calibration     |
| Dynamic Range              | > 90dB                    |
| Total Harmonic Distortion  | < 0.5%                    |
| Frequency Response         | 40Hz - 16kHz / $\pm 3$ dB |
| Packing Dimensions (WxHxD) | 436 x 104 x 324 mm        |
| Packing Gross Weight       | 2.0 kg                    |
| Receiver Power Supply      | DC12V, 500mA              |
| Receiver Consumption       | < 2W                      |
| Signal/Noise Ratio         | > 95dB                    |

WF-V11PD

## VHF PLUG AND PLAY WIRELESS MICROPHONE WITH BOBYPACK AND HEADSET (209.8 MHZ)

|                                  |                                        |
|----------------------------------|----------------------------------------|
| Receiving Sensitivity            | 10dBuV                                 |
| De-Emphasis                      | 75uS                                   |
| Audio Output Level               | Balanced 400mV; Unbalanced 400mV       |
| Receiver Size (WxHxD)            | 211 x 43 x 115 mm (antennas not incl.) |
| Antenna Length                   | 110 mm (min.) 430 mm (max.)            |
| Net Weight                       | 0.295 kg                               |
| Transmitter Power                | 10mW                                   |
| Modulation Type                  | FM                                     |
| Deviation                        | 37KHz                                  |
| Battery Voltage                  | 3V (2x1.5V AA-Type Batteries)          |
| Continuous Using                 | 7 hours                                |
| Pocket Trans. Dimensions (WxHxD) | 62 x 103 x 30 mm                       |
| Antenna (W/DxH)                  | Ø3 x 9 mm                              |
| Pocket Transmitter Net Weight    | 0.132 kg (batteries included)          |