DJM-S7

SCRATCH-STYLE 2-CHANNEL PERFORMANCE DJ MIXER

This new 2-channel battle mixer gives you the freedom to customize your setup and bring your own unique style to every performance. The unit enables free use of Serato DJ Pro and it’s a Hardware Unlock device for rekordbox, so you can use performance features in either application.

DJM-S7

b371eaa2-efe3-4a38-b47e-3bed9e6ba48f.png

bd128edf-3f7f-4234-a3d6-85be97b62d64.png

2837f6b1-300e-4644-8787-14aeed

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

DJM-S7

SCRATCH-STYLE 2-CHANNEL PERFORMANCE DJ MIXER

PRODUCT DETAILS

KEY FEATURES

Magvel Fader Pro
Boosted the rigidity of the knob mounting shaft in the vertical direction by 30% so you can scratch with even more confidence
8 Large performance pads
Large effect levers
Bluetooth input:wirelessly add audio from your phone
Loop MIDI: automated control of Dj software functions
USB hub
MIDI assignable via USB Type-B
Serato Dj Pro
Serato DVS
Pitch'n Time Dj
Recordbox
Colore: Nero

SPECIFICATIONS

MIDI control	assegnable
Compatible DJ Software	Unlocks Serato DJ Pro, rekordbox
DVS Control	Unlocks Serato DVS, rekordbox
Bluetooth Audio Input	standard version Bluetooth 5.0; Supported Codecs

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it

DJM-S7

SCRATCH-STYLE 2-CHANNEL PERFORMANCE DJ MIXER

Level Meter Size	9 segment
2 channels	
Frequency Range	20 - 20000 Hz
Power Supply	AC 100-240 V, 50 Hz / 60Hz
S/N Ratio USB	110 dB (USB), 103 dB (LINE), 88 dB (PHONO), 80 dB (MIC), 103 dB (AUX)
Distortion	0.003% (USB), 0.005% (LINE)
Power Consumption	24W
EQ/ISO	3 band
EQ/ISO Range	–8 dB to +6 dB
Reverse Channels	
Peak Limiter	
Auto BPM Counter	
Crossfader	Magvel Fader Pro, CURVE Assignable, Reverse Crossfader, Tension Adjustment
Mic Connection	XLR / 1/4-inch Jack Combo with Talkover Attenuator
Sound card	Connection USB (Type-B), Sample Rate 24 bit, Frequency 48 kHz
Inputs	2 LINE (RCA), 2 PHONO (RCA), 1 MIC (XLR & 1/4 inch TRS Jack), 1 AUX (RCA)
USB	2 USB A ports, 2 USB B ports,
Outputs	2 MASTER (XLR, RCA), 1 BOOTH (1/4 inch TRS Jack), 2 PHONES (1/4-inch stereo jack, 3.5-mm stereo mini-jack)
Sound Color FX	Filter, Dub Echo, Noise, Pitch, Wide Filter
Beat FX	Echo, Ducking Echo, Echo Out, Spiral, Helix, Delay, Reverb, Back Spin, One-shot Spin, Vinyl Brake, One-shot Brake, Flanger, Phaser, HP Filter, LP Filter, Trans, Kill, Roll, Fader Pitch, Fader Synth
Software System Requirements	Visit serato.com for its specifications; Visit rekordbox.com for its specifications

Via Enzo Ferrari 10
62017 Porto Recanati (MC), Italy
info@frenexport.it