

POKER-240A**240W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER****POKER-240A – Power, Flexibility, and Total Zone Control**

Meet the POKER-240A, a powerhouse **240W 4-zone mixer amplifier** designed for professional multi-room audio installations where performance and reliability are non-negotiable.

With **4 independent 70/100V zone outputs**, each equipped with a **dedicated 5-step attenuator plus Off**, you'll have precise control over every area. Need quick flexibility? Use the **Zone ON/OFF or ALL buttons** to manage coverage instantly.

Seamlessly blend speech and music with **3 Mic/Line inputs**, while **Mic 1 priority with adjustable voice-over** ensures announcements are always heard clearly. Add paging flexibility with **2 call station inputs** and full compatibility with the HMX-MIC paging microphone.

On the media side, the POKER-240A is a true all-in-one player: enjoy **DAB+ digital radio, FM tuner, USB, AUX, and Bluetooth® streaming**—all built right in. Plus, with stereo AUX input, stereo preamp out, and recording outputs, integration with external gear is effortless.

Designed for real-world installations, the POKER-240A also features a standby mode for energy savings without compromising readiness.

Whether it's for hospitality venues, retail, offices, or multi-zone public spaces, the **POKER-240A delivers crystal-clear audio, flexible zoning, and rock-solid reliability—all in one professional package.**



POKER-240A

240W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYEREco
Friendly19''
RackMulti
Zone

70/100V



48V



Bluetooth

dab+
DAB+

FM



USB



Wireless

POKER-240A

240W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER

PRODUCT DETAILS

KEY FEATURES

240W Power Amplifier

4-Zones with 70/100V Zone Outputs

Zone Attenuators with 5 positions + Off

Zone ON/OFF and ALL Buttons

3 Mic/Line Inputs

DAB+, USB, FM, AUX, Bluetooth Player

Priority on Mic 1 with Adjustable Voice Over

2 Call Station inputs

Compatible with HMX-MIC Paging Microphone

Stereo Aux In, Stereo Preamp and Rec Outputs

Standby function

SPECIFICATIONS

Power Supply AC 230V-50Hz (IEC)

Fuse T5AL 250V

Power Output 240W RMS

Amplifier Construction Class AB

Audio Source of Player USB / AUX / FM / DAB+ / BT

Inputs 3x Mic/Line (XLR/Jack), 1xaux (RCA)

POKER-240A

240W 4-ZONE MIXER AMPLIFIER WITH DAB+ PLAYER

Line output (REC)	RCA
Zone Outputs	Speaker
Phantom Power	+48V switchable inputs 1-3
Call Station input	2 x RJ45 (for optional HMX-MIC paging stations)
Mute	+24V relay contacts
THD	<0.5% @ 1kHz
Input impedance	1k Ohms (mic)/10k Ohms (line)
Input Sensitivity	-10dB (Line), -40dB (Mic)
SNR	70dB (Line), 70dB (Mic)
BT Version	5.0
Frequency Response	100Hz - 17kHz (-3dB)
Product Size (WxDxH)	433 x 288 x 89 mm (17.04 x 11.34 x 3.5 in.)
Product Size MAX (WxDxH)	485 x 317 x 97 mm (19.09 x 12.5 x 3.8 in.)
Weight	7.5 kg (16.53 lbs.)
Package Size (WxDxH)	545 x 395 x 149 mm (21.4 x 15.5 x 5.9 in.)
Package Weight	9.1kg (20.1 lbs.)