

ALCHEMIX 1203 PRO


**18 CHANNELS PROFESSIONAL MIXER WITH USB
PLAYER, BT PLAYER, EFFECT, COMPUTER INTERFACE**

This versatile mixer series is packed with everything you need to take your sound to the next level. With 18 channels (featuring 12 mic inputs and 3 stereo line inputs), it's built for both small gigs and mid-sized events. Enjoy 48V phantom power and a 75Hz low-cut filter on all mic inputs, ensuring clean and crisp sound.

Customize your mix with the 3-band EQ, two Aux Sends with pre/post selection, and plenty of flexibility with Mute, PFL-AFL, Sub, and L-R Assignments. For creative control, the built-in 24-bit, 16-preset professional effects engine lets you add the perfect touch to your sound, plus a handy Tap Tempo button.

Need to play some tracks? The Bluetooth and USB player give you full control with separate volume and assignments.

On top of that, you've got a high-quality USB soundcard for seamless 48kHz, 24-bit audio, plus a 7-band graphic EQ, 2 AUX returns, and soundcard playback control for even more fine-tuned adjustments and DAW integration. Whether you're mixing live or recording, this mixer has you covered with top-tier functionality and pro-level performance.



ALCHEMIX 1203 PRO

18 CHANNELS PROFESSIONAL MIXER WITH USB PLAYER, BT PLAYER, EFFECT, COMPUTER INTERFACE

PRODUCT DETAILS

KEY FEATURES

18 channels (12 mic inputs + 3 Stereo Line Inputs)

48V and 75Hz Low-cut on all Mic inputs

3-Band EQ, 2 Aux Send with Pre/Post selection

1 Effect bus, Mute, PFL-AFL, Sub and L-R Assignment

Bluetooth and USB Player with separate volume and assignments

USB Input/Output Sound Card (48kHz – 24-bit)

24-bit High-Quality Digital Effects with 16 adjustable presets and Tap Tempo button

7 Band graphic EQ, 2-Ch AUX Return, 2-Ch Subgroup, Soundcard playback control

SPECIFICATIONS

Configuration Channels	12 Mono Mic/Line, 3 Stereo Line
Max Input Level	Mic +10dBu / Line +22dBu
Max Output Level	XLR +22dBu, TRS +20dBu
Input Gain	Mic/Line +8~+54dB, Stereo Line 0~+10dB
Master Meter	-32dB to CLIP
Channel Meter	Signal LED Indicator
Frequency Response	20Hz to 22kHz ±1dB
CMRR (Mic 1kHz)	>75dB
THD+N (Total Harmonic Distortion+Noise)	<0.05%

ALCHEMIX 1203 PRO

**18 CHANNELS PROFESSIONAL MIXER WITH USB
PLAYER, BT PLAYER, EFFECT, COMPUTER INTERFACE**

Channel EQ	+/-15dB (High 12kHz), +/-15dB (Mid 2.5kHz), +/-15dB (Low 80Hz)
USB Audio	USB 2.0 / 2-Channel In/Out @ 48kHz
Supported Audio Formats	MP3/WAV/FLAC
DSP FX Processor	16 Presets, 24-bit/48kHz
Bluetooth	V 5.1
Power Requirements	100-240V~50/60Hz
Fuse Type	T1.6A H250V
Product Size (WxDxH)	530 x 340 x 85 mm
Product Weight	5.8 kg
Packing Size (WxDxH)	581 x 443 x 130 mm
Packing Gross Weight	6.4 kg