

REPO-MIC PAGING MICROPHONE FOR REPO-240A / REPO-350A MIXER AMPLIFIERS

The Repo-Mic is the ideal companion for all paging needs related to the use of the HELVIA Repo series mixers amplifiers. It is a gooseneck microphone with a microphone base powered by the Repo 240A / 350A central unit.



REPO-MIC PAGING MICROPHONE FOR REPO-240A / REPO-350A MIXER AMPLIFIERS

PRODUCT DETAILS

SPECIFICATIONS

Capsule	Back electret condenser
Polar Pattern	Cardioid
Control	Mic level, Page switch
Connectors	5-pin Phoenix (Euroblock)
Frequency Response (-3dB)	150Hz - 22kHz
Input Level Mic	-46dBV
Input Impedance Mic	600 Ohms
Output Level 10dBV	
Output Impedance balanced	600 Ohms
S/N Ratio	-60dB
Product Size (WxDxH)	100 x 141 x 445/52 mm (with Mic/without Mic) (3.94 x 5.55 x 17.52/2.05 in)
Product Weight	566 g. (1.25 lbs.)
Packing Size (WxDxH)	430 x 235 x 65 mm (16.93 x 9.25 x 2.56 in)
Packing Weight	1.01 kg (2.23 lbs.)