


DDJ-800

## 2-CHANNEL PORTABLE DJ CONTROLLER FOR REKORDBOX DJ

The DDJ-800 2-channel DJ controller is a pro DJ setup that's made to go wherever you do. This portable unit inherits the club-style layout and popular features of the DDJ-1000, including Color On Jog Displays, and packs it all into a lighter body. The result is a professional performance controller that you'll have no trouble transporting between gigs at weddings, parties and anywhere else you play. Stop worrying about MCs walking in front of the speaker thanks to the compatible Feedback Reducer feature in rekordbox dj. The system will automatically bring down the 'howling' sound from the mic – extra handy when you have 2 microphones plugged in at once. Use the DDJ-800 to mix audio from external sources, and apply Sound Color FX, Beat FX, EQs and Trim to make all of your shows unique.



DDJ-800

# 2-CHANNEL PORTABLE DJ CONTROLLER FOR REKORDBOX DJ

## PRODUCT DETAILS

### KEY FEATURES

Compact and portable

Color LCD On Jog Display located in the centre of each jog wheel

Feedback Reducer feature in rekordbox dj will instantly detect and reduce the 'howling' sound of microphone feedback

Club-style layout

Audio mixer feature

Feeling Adjust to customize the resistance of the jog wheels

Beat FX

Back lit Performance Pad

Plug and play

Key shift

Page feature to switch between displaying cues 1-8 and 1-16 at a touch to trigger each of them in a single track

### SPECIFICATIONS

**Channels** 2

**Deck** 4 / Dual  
**Control**

Jog Wheel

Feeling Adjust

**Beat FX** Echo, Multi Tap Delay, Spiral, Reverb, Trans, Flanger, Phaser, Pitch, Slip Roll, Roll, Enigma Jet, Mobius (Saw), Mobius (Triangle), Low Cut Echo

DDJ-800

# 2-CHANNEL PORTABLE DJ CONTROLLER FOR REKORDBOX DJ

<b>Colour FX</b>	Dub Echo, Filter, Noise, Pitch
<b>Sampler</b>	16slot x 4bank
<b>Hot Cues</b>	16
Auto Beat Loop, Beat Jump, Slip Mode, Talkover Function, Feedback Reducer, EQ Isolator	
Fader Start and Crossfader Curve Adjust	
<b>Inputs</b>	2 PHONO/LINE (RCA), 2 MIC (XLR & 1/4 inch TRS Jack, 1/4 inch TRS Jack), 1 AUX (RCA)
1 USB B port	
<b>Outputs</b>	2 MASTER (XLR, RCA), 1 BOOTH (1/4 inch TRS Jack), 2 HEADPHONE MONITOR (1/4 inch Stereo Phone Jack, 3.5mm Stereo mini-jack)
<b>Soundcard</b>	24 bit/44.1 kHz
<b>Frequency Range</b>	20 - 20000 Hz
<b>Signal-to-Noise Ratio</b>	111 dB
<b>Distortion</b>	< 0,003 % (USB)
Auto Stanby	
<b>Included DJ Software</b>	rekordbox dj
<b>DVS Control</b>	rekordbox dvs (not included)
<b>Software System Requirements</b>	Mac
<b>Dimensions (WxHxD)</b>	632x69,7x334x5 mm
<b>Weight</b>	4,7 kgs
<b>What's in the box</b>	DDJ-800, AC adapter, Power Cord, USB cableQuick Start Guide, rekordbox dj licence key card