

WF-U11PD UHF PLUG & PLAY WIRELESS MICROPHONE SYSTEM WITH BODYPACK AND HEADSET (FREQ. 865.00 MHZ)

SOUNDSATION WF-11 is the answer to all those who need a reliable, high-quality sound, and easy to use wireless microphone system. Ideal in educational, Portable Sound, Public Address, and DJ contexts, the WF-11 impresses with its brilliant and warm sound, thanks to the quality of components and the capsule designed for all application.









FRENEXPORT

Via Enzo Ferrari 10 62017 Porto Recanati (MC), Italy info@frenexport.it



WF-U11PD UHF PLUG & PLAY WIRELESS MICROPHONE SYSTEM WITH BODYPACK AND HEADSET (FREQ. 865.00 MHZ)

PRODUCT DETAILS

KEY FEATURES

UHF Transmission with SMD Technology		
4 available Frequencies in free-license ISM Europe Band		
Simple user Interface for plug and play setup		
30m ideal distance (without obstacles)		
Strong yet lightweight bodypack with professional headset microphone		
Professional and Lightweight Headset with high-sensibility dynamic cardioid capsule		

SPECIFICATIONS

Carrier Frequency	UHF 863-865MHz	
Available Frequencies	863.05 MHz, 864.15 MHz, 863.55 MHz, 865.00 MHz (WF-U11PD Freq. is 865.00 MHz)	
Frequency Stabilization	Automatic calibration	
Dynamic Range	> 90dB	
Total Harmonic Distortion	< 0.5%	
Frequency Response	40 – 18500 Hz / ±3dB	
Packing Dimensions (WxHxD)	436 x 104 x 324 mm	
Packing Gross Weight	2.0 kg	
Power Supply	DC12V, 400mA	
Consumption	< 4W	
Signal/Noise Ratio	> 95dB	

FRENEXPORT

Via Enzo Ferrari 10 62017 Porto Recanati (MC), Italy info@frenexport.it



WF-U11PD UHF PLUG & PLAY WIRELESS MICROPHONE SYSTEM WITH BODYPACK AND HEADSET (FREQ. 865.00 MHZ)

Border Upon Channel Rejection	> 80dB
Receiving Sensitivity	10dBuV
De-Emphasis	75uS
Audio Output Level	Balanced 400mV; Unbalanced 400mV
Dimensions (WxHxD)	211 x 43 x 115 mm (antennas not incl.)
Antenna	120 mm (not bent)
Net Weight	0.295 kg
Transmitter Power	10mW
Modulation Type	FM
Deviation	37KHz
Spurious Emission	> 30dB
Battery Voltage	3V (2x1.5V AA-Type Batteries)
Continuous Using	5 hours
Pocket Trans. Dimensions (WxHxD)	62 x 103 x 30 mm
Antenna (W/DxH)	Ø3 x 9 mm
Pocket Transmitter Net Weight	0.132 kg (batteries included)

FRENEXPORT

Via Enzo Ferrari 10 62017 Porto Recanati (MC), Italy info@frenexport.it