

Helvia

HRMA-1206 PLAY

120W 6-ZONES INTEGRATED MIXER AMPLIFIER WITH USB/SD/FM, AND ZONE INDIVIDUAL CONTROL



HRMA PLAY series offers 4 MIC inputs (MIC1 on front with Priority and Mute function; MIC 3 and 4 with Phantom), 3 AUX stereo line inputs, a USB/SD/FM player with remote control. They manage up to 6 Zones with individual attenuation control (6-step + Off). Speaker outputs are at 100V, plus a low-impedance main output. The HRMA series has a sturdy frame in two 19" rack units, and represent the ideal solution for shops, bars, pubs, restaurants, supermarkets and other small-medium sized venues with more than two zones. Powers range from 120W to 350W in total.



KEY FEATURES

6 zones outputs

Built-in USB/SD player and FM radio with remote control and built-in chime

4 MIC inputs (Mic 1 with priority and muting function)

MIC 2-4 with XLR (MIC3 and MIC4 with Phantom Power)

3 AUX line input and 1 AUX line output for power extension

Each AUX and MIC input has individual volume control

100V speaker outputs and 4-16ohm main output

MORE SPECIFICATIONS

Rated Output	120W
Output Regulation	Less than 3dB, from off-load to full load
Input sensitivity	Microphone: $\approx 3\text{mV}$ (unbalanced); Line: $\approx 300\text{mV}$ (unbalanced)
Frequency Response	80Hz-16kHz ($\pm 3\text{dB}$)
Distortion	Less than 1% (at 1kHz, 1/3 rated output voltage)
Signal to Noise Ratio	MIC: more than 71dB; LINE: more than 85dB
Tone	Bass: $\pm 10\text{dB}$ (at 100Hz); Treble: $\pm 10\text{dB}$ (at 10kHz)
FM	87.5MHz-108.0MHz
USB Connection	Type-B, Female
SD-Card	SD-Card Slot
USB/SD Drive Format	FAT32 format – max 32GByte
USB/SD File Formats	MP3 (44.1kHz/16bit @ 128Kbps)
Protection	DC voltage; overload; short-circuit
Mute	Input signals from MIC 1 override other input signals
Operation Voltage	AC 220-240V / 50Hz
Power Consumption	250W
Outer Packing Size (mm)	(L×W×H) 520×430×195
Unit Size (mm)	(L×W×H) 418×338×88
Gross Weight	13.5kg
Net Weight	11.5kg